



Black Line

Entry control for home and office

by Jantar



Capacitive switch button



Button D-C-R

- For unlocking the doors in access control systems with lower security level of two-way access control (for instance, Button can be used as an exit button instead of exit access control reader for unlocking the door-strike or opening sliding doors)
- An inexpensive way of basic two-way access control where one way access control is already implemented
- Button can also be used in any other application where a push button is needed
- Black Line family design
- LED and buzzer for signalization of the door strike status and sound warnings – self driven or controlled by access controller

TECHNICAL DATA

- **Dimensions: 64x10mm**
- **Capacitive touch distance: up to 4mm**
- **IP65 protection**
- **External power supply 9 to 14V DC**
- **Transistor output 500mA**
- **Max. current consumption 15mA**
- **Operating temperature: from -20 to +70°C**
- **LED and buzzer**
- **LED and buzzer control inputs (Button D-C-R only)**

ORDERING CODES

Code	Specification
BUTTON D-C-R	With LED and buzzer control input

Button D-C-R - with 6 wires flat cable (25cm)