



Entry control for home and office



Standalone RF receiver – REX A-4-B



Rex A-4-B with RF transmitter REMO

- Standalone access controller with built-in receiver for RF transmitters Remo
- For small, price-oriented access control systems
- Designed for private and public parking, garages, etc.
- For opening gates, barriers, shutters, for switching on/off alarm systems, etc.
- Suitable for mounting outdoors
- Internal memory for up to 1000 RF transmitters/buttons* /10.000 events
- Real time clock and RS-485 communication
- Anti-tamper alarm
- In standalone mode set-up can be made with a master transmitter, in advanced mode access control software (Blocker, Codeks) must be used
- Possible conversion to an advanced receiver with 26-bit Wiegand output.

TECHNICAL DATA

- **Dimensions:** 120x95x15 mm
- **Reading frequency:** 433 MHz
- **Receiving range:** up to 30 m
- **IP65 protection** – suitable for outdoor installation
- **Internal memory for 1000 ID devices*** / 10.000 events
- **External power supply** 9 to 14 V DC (Spider W5, Spider W5-B, Spider W40, Spider W40-B, Spider H20, Spider H20-B)
- **Push button and gate status inputs**
- **Built-in accelerometer (anti-tamper alarm)**
- **Transistor output (0,5 A)**
- **Current consumption up to 0,1 A**
- **Operating temperature:** from -20° to +50° C
- **LED and buzzer for gate status signalization**

* Each button of transmitter Remo is treated as a separate ID device!

ORDERING CODES

Code	Specification
REX A-4-B	RF receiver A-B type housing, 433 MHz
REMO E-0-B	RF transmitter in E-B housing, 433 MHz
REMO E-3-B	RF transmitter in E-B housing, 433 MHz, with built-in 13,56MHz Mifare DESFire tag

Rex A-4 - with 8 x 0,22 alarm cable (50 cm)