



Jantar

Entry control for home and office



Kit H1 for hotel and B&B applications (13,56 MHz)



Reader K-3-H



Rex X-3-H



- Hotel kit with reader with a keypad for room entrance control and hotel switch with card holder for switching of electricity in a hotel room
- In K/X A-type housing for surface installation
- For hotel rooms management
- Designed for hotels, B&B or rental apartments
- Reading frequency 13,56MHz
- RS-485 and Bluetooth communication (Reader K-3-H) and RS-485 and TCP/IP communication (Rex H-3-H)
- Internal memory for 20 cards and 1000 events (Rex K-3-H)
- Signalization of the door status by changing the color of the keypad (amber - locked, green - unlocked, red - error)
- Programming with Codeks Apartment Kit software or Codeks AC V10 / TA V10 + Codeks Hotel add-on

TECHNICAL DATA

- **Dimension: 90 x 90 x 17 mm (Reader K-3-H), 90 x 90 x 21 mm (Rex X-3-H),**
- **Reading frequency: 13,56 MHz**
- **Reading distance: up to 5cm**
- **Internal memory for 20 cards and 1000 events**
- **IP45 protection**
- **External power supply 9 to 14 V DC (Spider W5-B, Spider W40, Spider W40-B, Power H-20, Power H20-B)**
- **Anti-tamper alarm**
- **Operating temperature: from -20° to +40° C**
- **Max. current consumption: 0.2 A**
- **Signalization of the door status by changing the color of the keypad and buzzer**

ORDERING CODE

Code	Specification
KIT H1-3-4BNx	Hotel kit with access control reader with a keypad and hotel switch, 13,56 MHz, RS-485, TCP/IP and Bluetooth communication